



[Knowledgebase](#) > [easYgen-3000XT](#) > [How can I load older revision WSET setting files into recently upgraded easYgen-3000XT control with latest firmware](#)

How can I load older revision WSET setting files into recently upgraded easYgen-3000XT control with latest firmware

Clemens - 2024-09-27 - [easYgen-3000XT](#)

How to use (and prepare/update) old WSET Files into newer firmware revision of easYgen-3000XT control ?

Load old WSET -3000 .wset file

- Open ToolKit version 6.4 or higher
- Go to TAB [Settings] and Click [Associate w/ Application] → Window appears
- Select thewset file to be updated and Click »Next >«
- Select the XT- .sid file and Click »Next >«
- Define name and location/folder of new .wset file where settings will be saved to and Click »Next >« → Now it will take some seconds
 - If settings conversion is installed between the original software version and the target version defined by the target *.sid file (which comes with installing the tool for this particular easYgen version), an automated settings conversion will be started. Settings differences will be detected and resolved. If resolving was not possible, a list with information and possible warnings is displayed. This information is also available in \\ProgramData\Woodward\ToolKit\SettingsConversion\conversionlog.txt on the PC
 - If settings conversion is not possible between the original software version and the target version defined by the target *.sid file, a manual conversion is initiated. For this, a dialog "Settings Differences" will be opened:
 - Go through the left hand side list and select settings found
 - If possible, ToolKit offers you to »Map« the setting for easYgen-XT. Every mapped setting is listed below
 - Close mapping with a click on »OK« button and
 - back on »Settings Differences« screen - with »Next >« button
 - Click »OK«
 - The settings conversion information is stored in the file "conversionlog.txt" and in the files .txt at \\ProgramData\Woodward\ToolKit\SettingsConversion