



## Ring Bus application with more than 32 generators

Clemens - 2022-10-20 - GC-3400XT-P1

Do you want to build a

### **Ring Bus application with +32 generators and many more?**

Here is how to connect +32 generators:



One GroupController GC3400XT is added to each powerplant and used as smart an IED (intelligent electronic device) load share gateway collecting all easYgen-3500XT within this group.

No need to connect current and voltage sensing but can be wired.

GC-3400XT's Group breaker is always seen as closed, as there is no physical group breaker

All GC3400XT communicating via Ethernet B & C redundant Ethernet to other GC-3400XTs.

Each GroupController communicate via CAN Ethernet A to each easYgen-3500XT within the group.

Each GroupController can placed within the group where it is convenient.

GroupControllers LDSS (Load dependent start & stop) functionality can be used to sequence individual gensets within each group.



Layer 1 n+1 easYgen-3500XT controls within one group are connected to above GC-3400XT in Layer 2.

Ring Bus Couplers & incoming Mains Feeders can be served by LS-6XT in Layer 3 as well:



Layer 1 n+1 easYgen-3500XT controls within one group are connected to above GC-3400XT in Layer 2

Documentation GroupController

[https://wss.woodward.com/manuals/PGC/easYgen-3000XT\\_series/easYgen%20%20GC-3000XT](https://wss.woodward.com/manuals/PGC/easYgen-3000XT_series/easYgen%20%20GC-3000XT)